



Product Description: MR16 Emergency Back Up


50W/VA (1 hour) and 20W/VA (3 hour) Low Voltage Train Halogen Emergency backup.

SKU Code	Wattage	Finish Colour	SKU Type
AU-EMTR50W	50	White	Emergency

Line Drawing

Polar Curve

Colour



Feature & Benefits

- Maintained low voltage lighting train to operate 12V tungsten halogen lamps in the event of power failure (lamp supplied at 6V)
- Includes 60VA electronic transformer, low voltage lampholder and LED charge indicator
- Can be installed through a 60mm ceiling cut-out
- Provides 3 hour back-up duration with a 20W MR16 lamp or 1 hour duration with a 50W MR16 lamp

Product Specs:

Input Voltage	220~240V AC	Power Factor	0.92
Width (mm)	260	Length (mm)	800
Weight (Kg)	1.986	Height (mm)	95
Product Type	Emergency	Cutout Diameter (mm)	60-

Compliance & Approvals:



Warranty:

This product has a warranty period of 1 Year. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.