



Product Description: QuaZarPIR™ 10W Adjustable IP65 Driverless Floodlight


Addition to the QuaZar™ floodlight range is the QuaZarPIR™. Maintaining the popular slim design, the inclusion of a PIR incorporates the function of motion detection, without compromising the product's popular appearance. The PIR has been specially designed to help reduce false triggering; both the position and functions can be fully adjusted to suit any application. Ideal for both domestic and commercial applications, the QuaZarPIR™ is perfect for security lighting as well as helping to reduce energy costs.

SKU Code	Wattage	Colour	Lumens	Lumens/Watt	Beam Angle	Finish Colour	SKU Type
EN-FLH10PBLK/30	10	3000	900	90	120	Black	PIR
EN-FLH10PBLK/40	10	4000	900	90	120	Black	PIR
EN-FLH10PW/30	10	3000	900	90	120	White	PIR
EN-FLH10PW/40	10	4000	900	90	120	White	PIR

Line Drawing

Polar Curve

Colour



Black

White

Feature & Benefits

- IP65 rated with ultra slim design and adjustable PIR sensor
- PIR detection distance up to 10m and detection range of 120°
- PIR mode selector dials to adjust daylight, time and sensitivity
- Available in black and white finish housing
- Pre-wired with 800mm of cable
- 1.5kV surge protection
- 3 year warranty

Product Specs:

Input Voltage	180~265V AC	Input Frequency	50/60HZ
Power Factor	0.8	IP Rating	IP65
Lifetime L70 (hrs)	25000hrs	IK Rating	IK08
Lamp Base	None	Width (mm)	121
Weight (Kg)	0.457	Height (mm)	93
Product Type	Floodlights		

Compliance & Approvals:



Warranty:

This product has a warranty period of 3 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.