






Product Description:

QuaZarPIR™ 20W Adjustable IP65 Driverless Floodlight

Addition to the QuaZar<sup>TM</sup> floodlight range is the QuaZarPIR<sup>TM</sup>. Maintaining the popular slim design, the inclusion of a PIR incorporates the function of motion detection, without compromising the product's popular appearance. The PIR has been specially designed to help reduce false triggering; both the position and functions can be fully adjusted to suit any application. Ideal for both domestic and commercial applications, the QuaZarPIR<sup>TM</sup> is perfect for security lighting as well as helping to reduce energy costs

SKU Code	Wattage	Colour	Lumens	Lumens/Watt	Beam Angle	Finish Colour	SKU Type
EN-FLH20PBLK/30	20	3000	1800	90	120	Black	PIR
EN-FLH20PBLK/40	20	4000	1800	90	120	Black	PIR
EN-FLH20PW/30	20	3000	1800	90	120	White	PIR
EN-FLH20PW/40	20	4000	1800	90	120	White	PIR

#### Colour





### Feature & Benefits

- IP65 rated with ultra slim design and adjustable PIR sensor
- PIR detection distance up to 10m and detection range of
- PIR mode selector dials to adjust daylight, time and sensitivity
- Available in black and white finish housing
- Pre-wired with 800mm of cable
  3 year warranty
- 1.5kV surge protection

## **Product Specs:**

Input Voltage	180~265V AC
Power Factor	0.8
Lifetime L70 (hrs)	25000hrs
Lamp Base	None
Weight (Kg)	0.761
Product Type	Floodlights
Operating Temp. (Max) °C	40°C

Input Frequency	50/60HZ
IP Rating	IP65
IK Rating	IK08
Width (mm)	168
Height (mm)	129
Operating Temp. (Min) °C	-30°C

# Compliance & Approvals:





















This product has a warranty period of 3 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.