

Lighting design guide

How to use the ready reckoner lux planner

1. Select the fitting
2. Choose the Lux Level you require
3. Select the closest room dimensions of the space
4. Use the table to determine the quantity of fittings required

Recommended Lighting Levels Explained

200 Lux - For general occupancy

300 Lux - For moderately easy tasks

500 Lux - For moderately difficult tasks

Design criteria all downlights and LED panel

1. All dimensions shown are in metres
2. Ceiling height assumed @ 2500mm
3. Average Surface Reflectances used - Floor 20 / Walls 50 / Ceiling 70
4. Working Plane measured at 750mm above FFL
5. Maintenance Factor assumed @ 0.80



E6^{PRO}
200 & 300 Lux
EN-DE6PRO/40

Watts 6
Lumens 620

Room Size		Choose Lux Level	
L (m)	W (m)	200 lux	300 lux
2.5	2.5	4	5
2.5	5	6	10
2.5	7.5	10	14
2.5	10	12	18
5	5	12	16
5	7.5	18	24
5	10	21	32
7.5	7.5	25	36
7.5	10	32	45
10	10	42	56



E5TM
200 & 300 Lux
EN-DE5

Watts 4.5
Lumens 400

Room Size		Choose Lux Level	
L (m)	W (m)	200 lux	300 lux
2	2	4	6
2	4	8	12
2	6	10	15
2	8	12	18
4	4	12	20
4	6	-	-
4	8	-	-
6	6	-	-
6	8	-	-
8	8	-	-



E8TM
200 & 300 Lux
EN-DE8

Watts 8
Lumens 580/620

Room Size		Choose Lux Level	
L (m)	W (m)	200 lux	300 lux
2.5	2.5	4	5
2.5	5	6	10
2.5	7.5	10	14
2.5	10	12	18
5	5	12	16
5	7.5	18	24
5	10	21	32
7.5	7.5	25	36
7.5	10	32	45
10	10	42	56



Lumi-FitTM
200, 300 & 500 Lux

	EN-DDLH413	EN-DDLH618	EN-DDLH818	EN-DDLH825	EN-DDLH840	EN-DDLH1045
Watts	13	18	18	25	40	45
Lumens	1260	1800	1900	2600	4150	4500

Room Size		Choose Lux Level											
L (m)	W (m)	200 lux	300 lux	200 lux	300 lux	200 lux	300 lux	200 lux	300 lux	300 lux	500 lux	300 lux	500 lux
2.5	2.5	3	4	2	3	2	3	1	2	1	2	1	2
2.5	5	4	6	3	4	3	4	2	3	2	3	2	3
2.5	7.5	5	8	4	5	4	5	3	4	3	4	3	4
2.5	10	6	10	5	7	5	7	4	5	4	5	4	5
5	5	6	9	6	8	6	8	4	5	4	5	4	5
5	7.5	8	15	8	10	8	10	5	8	5	8	5	8
5	10	12	18	8	12	8	12	6	10	6	10	6	8
7.5	7.5	12	20	9	15	9	15	8	12	6	12	6	9
7.5	10	16	24	12	18	12	18	9	15	9	15	9	12
10	10	24	36	16	24	16	24	12	16	12	16	12	16

X = Specific luminaire not suitable to achieve LUX level in room size

For assistance please email us on uk@enlitemlighting.com

Notes

The lighting calculation information displayed above is an indicative guide for the areas and design criteria indicated. It is recommended that the customer carries out his own calculations to verify that the proposed quantity of luminaires meet the specified requirements. All quantities shown are calculated and rounded upwards and then determined into an amount that offers a grid pattern for installation. Enlite does not accept responsibility for lighting installations which fail to comply with specification where this criteria has been used to estimate quantity.