

Product Description: T8 30W 1800mm Lamp

These LED T8 Tubes are a direct retrofit replacement for existing T8 tubes. They can be simply swapped with the simple instructions supplied alongside the starter unit supplied with each tube.

SKU Code	Colour	Lumens	Lumens/Watt	Wattage	Beam Angle	CRI
AU-RT81830FR/40	4000	3000	100	30	120	80

Line Drawing

Polar Curve

Colour

Feature & Benefits

- 100lm/W high brightness LED retrofit tube with rotatable end caps
- Up to 70% energy saving compared to traditional fluorescent tubes
- 120 degree beam angle for even focused light distribution
- LED Starter allows for safe lamp replacement (starter included)
- Instant start, no flickering, no humming
- (L70) at a 50,000 hour lifetime
- 5 Year Warranty - see www.auroralighting.com

Product Specs:

Input Voltage	100~240V AC	Power Factor	0.9
Overall Diameter (mm)	32	Lamp Base	G13
Weight (Kg)	0.445	Lifetime Hours	50000hrs

Compliance & Approvals:

✓ RoHS

Warranty:

This product has a warranty period of 1 Year. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.