




**Product Description:** EcoT8<sup>™</sup> 1800mm 51W IP20 Twin T8 Batten


The range of EcoT8<sup>™</sup> integrated open LED battens looks so close to traditional T8 and T5 open style fluorescent fittings, you won't be able to tell they are LED. Perfect for retrofit or new build, they've been designed specifically to mimic traditional fittings. Maintenance free and available in single or twin with or without reflector, now you can upgrade and benefit from all the advantages of LED technology while maintaining existing look and feel of traditional fluorescent.

SKU Code	Wattage	Colour	Lumens	Lumens/Watt	Beam Angle	Finish Colour	SKU Type
EN-BT1851/40	51	4000	4500	89	120	White	Non Dimmable


**Line Drawing**



**Polar Curve**



**Colour**



White

## Feature & Benefits

- Steel housing and high quality polycarbonate diffuser eliminate hot spots providing uniformed low glare light output
- Perfect for retrofitting existing installations or as an alternative to T8 or T5 fluorescent fittings
- Twin version available with winged reflectors for reduced glare
- Through wiring with side and rear cable entry
- Integrated driver supplied in housing
- Available in typical 1200mm, 1500mm and 1800mm lengths
- 1.5kV surge protection
- 3 years warranty

## Product Specs:

Input Voltage	220~240V AC	Input Frequency	50/60HZ
Power Factor	0.95	IP Rating	IP20
Lifetime L70 (hrs)	35000hrs	IK Rating	IK05
Lamp Base	Other	Width (mm)	85
Length (mm)	1820	Weight (Kg)	2.531
Height (mm)	35	Product Type	Linears
Operating Temp. (Min) °C	-55°C	Operating Temp. (Max) °C	30°C

## Compliance & Approvals:



## Warranty:

This product has a warranty period of 3 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.