


## Product Description: 60-400W 1 Gang 2 Way Zero Cross Rotary Dimmer Module

1 Gang 2 Way Zero Cross Rotary Dimmer Module

| SKU Code |
| --- |
| EN-DSP400X |

## Line Drawing




## Polar Curve

## Colour

## Feature & Benefits

- Suitable for control of dimmable LED lamps, dimmable electronic transformers, dimmable LED drivers, toroidal transformers and tungsten lamps
- Integrated trimming potentiometer allows lamps to be set at a minimum level to prevent them going out or flickering at the bottom of the dimmer range
- Leading edge phase control
- For use with resistive and inductive loads
- Integrated over-temperature protection fuse
- 1 Year Warranty

## Product Specs:

| | | | |
|---|---|---|---|
| Input Voltage | 220~240V AC | Width (mm) | 25 |
| Length (mm) | 62 | Weight (Kg) | 0.054 |
| Height (mm) | 48 | | |

## Compliance & Approvals:

## Warranty:

This product has a warranty period of 1 Year. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase.The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.