



**Product Description:** LEDLine<sup>™</sup> 14.4W CRI90 Flexible Strip


Single colour flexible CRI90 LED strip delivering up to 1400lm per metre with self-adhesive backing (must be applied to clean surfaces). Perfect for retail applications where higher colour rendering is needed to distinguish and enhance certain colours. With a beam angle of 120° individual light points are less visible creating a continuous glow. This strip has cut points every 100mm for maximum flexibility what length is concerned. Maximum run of 10m, any length over 10m must be run in parallel. Low power consumption of 14.4W per metre. Strip can be cut to length and 2m leads soldered to special order. A 24V DC Constant Voltage LED driver is required (see driver options table). Reel length 30m.

SKU Code	Wattage	Colour	Lumens	Lumens/Watt	Beam Angle	Finish Colour
EN-ST903/30	14.4	3000	1200	84	120	White
EN-ST903/40	14.4	4000	1300	91	120	White

## Line Drawing

## Polar Curve

## Colour



## Feature & Benefits

- CRI90 flexible LED strip with 3M™ self adhesive backing
- CRI90 brings out the true colour of objects and surroundings
- Cut points every 100mm for maximum flexibility
- Beam angle of 120° and 17mm between LEDs, 60 LEDs/m
- Maximum length of run 10m
- For runs over 10m lengths to be connected in parallel
- Reel length 30m
- Requires 24V DC Constant Voltage LED driver
- 3 year warranty

## Product Specs:

Input Voltage	24~V DC	IP Rating	IP20
Lifetime L70 (hrs)	30000hrs	Width (mm)	10
Height (mm)	2	Product Type	LED Strip

## Compliance & Approvals:



## Warranty:

This product has a warranty period of 3 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.