






Product Description:

LEDLine™ 22W CRI90 Flexible Strip

Single colour flexible CRI90 LED strip delivering up to 2400lm per metre with self-adhesive backing (must be applied to clean surfaces). Perfect for retail applications where higher colour rendering is needed to distinguish and enhance certain colours. With a beam angle of 120° individual light points are less visible creating a continuous glow. This strip has cut points every 55mm for maximum flexibility what length is concerned. Maximum run of 10m, any length over 10m must be run in parallel. Low power consumption of 22W per metre. Strip can be cut to length and 2m leads soldered to special order. A 24V DC Constant Voltage LED driver is required (see driver options table). Reel length 30m.

SKU Code	Wattage	Colour	Lumens	Lumens/Watt	Beam Angle	Finish Colour
EN-ST904/30	22	3000	2300	105	120	White
EN-ST904/40	22	4000	2400	110	120	White



Feature & Benefits

- CRI90 flexible LED strip with 3M[™] self adhesive backing
- CRI90 brings out the true colour of objects and surroundings
- Cut points every 55mm for maximum flexibility
- Beam angle of 120° and 8mm between LEDs, 126 LEDs/m
- Reel length 30m
- For runs over 5m lengths to be connected in parallel
- Requires 24V DC Constant Voltage LED driver
- 3 Year Warranty

Product Specs:

Input Voltage	24~V DC	IP Rating	IP20
Lifetime L70 (hrs)	30000hrs	Width (mm)	12
Height (mm)	2	Product Type	LED Strip

Compliance & Approvals:













Warranty:

This product has a warranty period of 3 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.