



Product Description: Esofit Plus 15W 5-6" Surface Mount Trim

Designed to service the needs of the residential/commercial market, the Aurora Esofit Plus surface mount retrofit 5-6" trim is ideal for replacing existing incandescent, fluorescent and halogen lights with their superior high powered low wattage LEDs with CRI>90 for true color rendering. The Esofit Plus installs easily into most Junction Boxes and 5-6" recessed CANs, including IC and NON-IC housings offering great versatility between different project requirements. Compatible with most line voltage dimmers.

SKU Code	Wattage	Colour	Lumens	Lumens/Watt	Beam Angle	Finish Colour
AR-SMDLA56/27	15	2700	950	64	110	White
AR-SMDLA56/30	15	3000	1045	70	110	White
AR-SMDLA56/40	15	4000	1045	70	110	White

Line Drawing

Polar Curve

Colour

Feature & Benefits

- Fits most Junction boxes and 5- 6" CANS
- Light aluminum body with ventilation slot for superior heat dissipation
- Easy installation - E26 socket & quick connector
- 120V inline voltage dimmable
- Power factor >0.9
- IC rated (when used with an IC rated CAN)
- Compression springs provided within the pack
- High Color Rendering of CRI>90
- Suitable for use in Wet locations
- Energy Star accredited
- Title 24 High Energy compliance for California
- (L70) at 40,000 hour lifetime
- 5 year warranty

Product Specs:

Input Voltage	120~120V AC	Input Frequency	60/60HZ
Power Factor	0.90	IP Rating	Wet Location
Lifetime L70 (hrs)	40000hrs	Lamp Base	E26
Overall Diameter (mm)	185	Height (mm)	33.02
Product Type	Downlights	Cutout Diameter (mm)	101-152
Operating Temp. (Min) °C	-20°C	Operating Temp. (Max) °C	40°C

Compliance & Approvals:



Warranty:

This product has a warranty period of . Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.