



Product Description: 4.4W CRI90 Tape

24V DC single color, flexible CRI>90 LED strip delivering up to 427lm per foot with self-adhesive backing (always apply to clean surfaces). Perfect for retail applications where higher color rendering is needed to distinguish and enhance certain colors. With a beam angle of 120° individual light points are less visible creating a continuous glow. This strip has cut points every 3.93" / 100mm for maximum flexibility what length is concerned.

Maximum run of 19.7ft / 6m, any length over 19.7ft / 6m must be run in parallel. Low power consumption of 4.4W per foot. A 24V DC Constant Voltage LED driver is

SKU Code	Wattage	Colour	Lumens	Lumens/Watt	Beam Angle	Finish Colour
AR-ST903/30	4.4	3000	366	84	120	White
AR-ST903/40	4.4	4000	396	90	120	White
AR-ST903/60	4.4	6000	427	98	120	White

Line Drawing

Polar Curve

Colour

Feature & Benefits

- Single colour flexible LED strip with self adhesive backing (must be applied to clean surfaces)
- Cut points every 100mm
- 17mm between LEDs
- Beam angle 120°
- Maximum length of run 10m
- For runs over 10m individual lengths should be connected in parallel
- Requires 24V DC Constant Voltage LED driver
- Low power consumption - 14.4W per metre
- Dimmable with 0-10V Dimmer.
- Please order to the nearest foot. (Reel length 23' / 7m)
- 3 Year Warranty - see www.auroralighting.com for details

Product Specs:

Input Voltage	24~24V DC	IP Rating	Dry Location
Lifetime L70 (hrs)	30000hrs	Width (mm)	10
Weight (Kg)	0.174	Height (mm)	2
Product Type	LED Strip		

Compliance & Approvals:



Warranty:

This product has a warranty period of 3 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.