




Product Description: AOne[™] 16A On/Off Inline Relay

This AOne[™] 16A Relay fits inline with any device up to 16A for on/off control. This product features live energy monitoring to 0.1 Watt accuracy via the AOne[™] App allowing you to monitor energy consumption from anywhere in the world. Install in an IP rated box for use outdoors.

SKU Code	Finish Colour
AU-A1ZBR16A	White

Line Drawing **Polar Curve** **Colour**



White

Feature & Benefits

- On/Off control
- Live power monitoring typically within 2-3% accuracy
- Ability to be controlled individually or within a space
- Can be used in lighting scenes and within lighting schedules
- Overload and over temperature protection
- Works with different sized cables, max. cable dia. of 11.8mm
- For outdoor use an IP rated enclosure is required
- 2 Year Warranty

Product Specs:

Input Voltage	220~240V AC	Width (mm)	36
Length (mm)	108	Weight (Kg)	0.072
Height (mm)	24		

Compliance & Approvals:



Warranty:

This product has a warranty period of 2 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.