




Product Description:

QuaZar™ 20W Adjustable IP65 Driverless LED Floodlight


The IP65 driverless range of QuaZar™ floodlights incorporate the latest in high voltage LED technology. With their ultra slim profile and high performance, now you can light your external areas and gardens without sacrificing the appearance. Available in 10W, 20W, 30W and 50W versions including black and white housing finishes to suit external fascias.

SKU Code	Wattage	Colour	Lumens	Lumens/Watt	Beam Angle	Finish Colour	SKU Type
EN-FLHV20BLK/30	20	3000	2000	100	120	Black	Non Dimmable
EN-FLHV20BLK/40	20	4000	2000	100	120	Black	Non Dimmable
EN-FLHV20BLK/65	20	6500	2000	100	120	Black	Non Dimmable
EN-FLHV20W/30	20	3000	2000	100	120	White	Non Dimmable
EN-FLHV20W/40	20	4000	2000	100	120	White	Non Dimmable
EN-FLHV20W/65	20	6500	2000	100	120	White	Non Dimmable

Line Drawing



Polar Curve



Colour

Feature & Benefits

- IP65 rated LED floodlight with ultra slim design for minimal visual impact
- Mains voltage LED chips - no driver for improved reliability
- IK08 rated aluminium housing and tempered glass provides excellent protection
- Available in black and white finish housing
- Pre-wired with 600mm of cable
- 1.5kV surge protection

Product Specs:

Input Voltage	180~240V AC	Input Frequency	50/60HZ
Power Factor	0.8	IP Rating	IP65
Lifetime L70 (hrs)	25000hrs	IK Rating	IK08
Lamp Base	None	Width (mm)	181
Weight (Kg)	0.608	Height (mm)	125
Product Type	Floodlights	Operating Temp. (Min) °C	-20°C
Operating Temp. (Max) °C	40°C		

Compliance & Approvals:



Warranty:

This product has a warranty period of 3 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.