



## Product Description: 11W 5-6" Retrofit Downlight


Designed to meet the needs of the retail market, the Aurora Esokit HV LED retrofit 5-6" downlight is ideal for replacing existing incandescent or halogen downlights with its superior high powered low wattage LEDs. The Esokit range installs easily into most standard 5-6" recessed CANs, including IC and NON-IC housings and it is for both new and retrofit construction. It consumes only 11 Watts of power with 800 lumen output. Compatible with most household dimmers.

SKU Code	Wattage	Colour	Lumens	Lumens/Watt	Beam Angle	Finish Colour
AR-DL1156/27	11	2700	800	73	80	White

## Line Drawing

## Polar Curve

## Colour



## Feature & Benefits

- Fits most 5-6" CANS
- Easy installation - E26 socket & quick connector
- Flicker Free - Compatible with most household dimmers
- High power HV LED light engine
- Light aluminum body with superior heat dissipation
- Power factor >0.9
- IC rated (when used with an IC rated CAN)
- High Color Rendering - CRI > 80
- ENERGY STAR
- Can be used for California Title 24 High Energy Compliance
- Suitable for wet locations
- (L70) at a 40,000 hour lifetime
- 5 Year Warranty

## Product Specs:

Input Voltage	120~120V AC	Input Frequency	50/60HZ
Power Factor	0.9	IP Rating	IP65
Lifetime L70 (hrs)	40000hrs	Lamp Base	E26
Overall Diameter (mm)	185	Weight (Kg)	0.21
Height (mm)	92	Product Type	Downlights
Cutout Diameter (mm)	121-150	Operating Temp. (Min) °C	-20°C
Operating Temp. (Max) °C	40°C		

## Compliance & Approvals:



## Warranty:

This product has a warranty period of . Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.