

**Product Features:**

- Maintained or Non-maintained low voltage lighting pack to operate 12V tungsten halogen lamps in the event of power failure (lamp supplied at 6V)
- 3 hours of low voltage lighting in the event of mains power failure
- Non-maintained / maintained via remote transformer (not supplied)
- LED indicates charger in operation (LED may be remote mounted)
- 6-Volt, sealed lead-acid maintenance free rechargeable battery
- Unit may be wall mounted above or below false ceilings
- Suitable for 1 x 50W load
- Safety compliance – EN 61347-1, EN 61347-2-27, EN 60598-2-22
- EMC compliance – EN 55015, EN 61000, EN 61547+A1
- 5 Year guarantee (excludes battery)

**Product Image:**



50 3


**Product Specs:**

Input Voltage	220~250V AC	Width (mm)	177
Length (mm)	72	Weight (Kg)	3.04
Case Cover Colour	White		

**SKU Table and Ordering:**

SKU Code	Lumens/Watt
AU-ELP50	0

**Compliance & Approvals:**



**Warranty:**

This product has a warranty period of 1 Year. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.