

Product Description:

The m7™ fixed, integrated, fire rated 6W LED downlight with new improved design featuring enhanced thermal management, integrated IC cap and improved efficacy with driver-on-board and high voltage LED chips. Available in 2700K, 3000K and 4000K. Interchangeable bezels available in White, Matt White, Polished Chrome and Satin Nickel. Fitted with 40° lens. FastRFix™ rapid install system connector included. Rated to 30, 60 and 90 minute fire ceilings. Complies with BS EN 1365-2: 2014 (fire resistance), BS EN ISO 10140-2: 2010 & BS EN ISO 10140-3: 2010 + A1: 2015 (acoustics), BS EN 13141-1:2400 (Air leakage).

5 year extended warranty - register at auroralighting.com/warranty

Product Features:

- BS EN 1365-2: 2014 (fire resistance)
- BS EN ISO 10140-2: 2010 & BS EN ISO 10140-3: 2010 + A1: 2015 (acoustics)

Product Specs:


Technology	LED	Input Voltage	220~240V AC
LED Chip	2835	Number of LEDs	6
Positional Adjustment	Fixed	Input Frequency	50/60HZ
Lifetime L70 (hrs)	40000	Power Factor	0.95
Dimmable	No	Luminaire Distribution	Direct
Positional Adjustment	Fixed	IP Rating	IP65
Fire Protection	Yes	Acoustic Rated	Yes
SDCM	5	Operating Env. Temp. (Min) °C	-20°C
Operating Env. Temp. (Max) °C	25°C	Optic Material	PMMA
Overall Diameter (mm)	78	Cutout Diameter (mm)	60
Recess Depth (mm)	73	Weight (Kg)	0.266

Product Image:



m7™ 6W IP65 Fixed Non-Dimmable Fire Rated Downlight

Line Drawing




SKU Table and Ordering:

SKU Code	Wattage	Colour	Lumens	Lumens/Watt	Beam Angle
AU-FRL701B/30	6	3000	430	72	40
AU-FRL701B/40	6	4000	460	77	40

Accessories:

SKU Image	SKU Code	Description
	AU-BZ700	m7™ Bezel
	AU-BZ703	m7™ Bezel

	AU-FRLM10EM	3 Hour Maintained Emergency Pack
---	-------------	----------------------------------

Warranty:

This product has a warranty period of 1 Year. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.