



**Product Description:** 2x9W 1-10V Dimmable 350mA Constant Current Driver

1-10V Dimmable 350mA Constant Current LED Driver.  
Use AU-DSPLD 1-10V Dimmer to control (up to 40 - AU-LEDD16CC).  
350mA Constant current output.


SKU Code

AU-LEDD16CC

Line Drawing

Polar Curve

Colour



## Feature & Benefits

- Dimmable constant current LED driver for use with 350mA LEDs
- Use AU-DSPLD 1-10V Dimmer to control (up to 25 - AU-LEDD16CC)
- 350mA Constant current output
- 2 series circuits with 1-9 LEDs each
- Overload protection
- Short-circuit protection
- Thermal protection
- Loop-in, loop-out primary wiring terminals
- Integrated earth terminal for earth continuity
- No junction box required
- 1.0kV SURGE PROTECTION – EN 61547
- Safety compliance - EN 61347
- EMC compliance - EN 55015, EN 61000, EN 61547
- Dimmable
- Series wiring only
- 3 Year Warranty - see [www.auroralighting.com](http://www.auroralighting.com) for details

## Product Specs:

|               |             |             |       |
|---------------|-------------|-------------|-------|
| Input Voltage | 220~240V AC | Width (mm)  | 38    |
| Length (mm)   | 169         | Weight (Kg) | 0.120 |
| Height (mm)   | 28          |             |       |

## Compliance & Approvals:



## Warranty:

This product has a warranty period of 1 Year. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.